

# Manual Supplement

Manual Title:	6003A Operators	Supplement Issue:	<b>2</b>
Print Date:	July 2014	Issue Date:	3/17
Revision/Date:		Page Count:	12

---

---

This supplement contains information necessary to ensure the accuracy of the above manual.  
This manual is distributed as an electronic manual on the following CD-ROM:

CD Title:	6003A
CD Rev. & Date:	8/2014
CD PN:	4406558

**FLUKE**®

**Calibration**

## Change #1, 371, 372, 373, 393, 400, 402, 405, 407, 415, 494

Replace the entire **Specifications** section, pages 1-5 through 1-14.

### Specifications

This section gives the general and detailed specifications of the Product.

#### Input Power

Voltage	115 V, 230 V, 200 V (Japan) $\pm 10\%$
Frequency	47 Hz to 63 Hz
Maximum consumption	2250 VA max

#### Dimensions

Height	415 mm (16.3 inches)
Height (without feet)	402 mm (15.8 inches)
Width	430 mm (16.9 inches)
Depth	640 mm (25.2 inches)
Weight	62 kg (136 lb)

#### Environment

Operating temperature	5 °C to 40 °C
Calibration temperature (Tcal) range	21 °C to 25 °C
Storage temperature	-10 °C to 55 °C
Transit temperature	-15 °C to 60 °C
Warm up time	1 hour
Safe operating max. relative humidity (non-condensing)	<80 %, 5 °C to 31 °C ramping linearly down to 50 % at 35 °C
Storage max. relative humidity (non-condensing)	<90 %, -10 °C to 55 °C
Operating altitude	2,000 m maximum
Storage altitude	12,000 m maximum
Shock	MIL-PRF-28800F class 3
Vibration	MIL-PRF-28800F class 3
Enclosure	MIL-PRF-28800F class 3

#### Safety

IEC61010-1, IEC 61010-2-030, Overvoltage category II, Pollution Degree 2

#### EMC

IEC 61326-1, Controlled

#### General Electrical

Voltage/Current amplitude setting resolution	5.5 digits
Range of fundamental frequencies	15 Hz to 1 kHz
Line frequency locking	45 Hz to 65.9 Hz at user discretion
Frequency accuracy	$\pm 50$ ppm
Frequency setting resolution	0.001 Hz for 15 Hz to <500 Hz, 0.01 Hz 500 Hz to 1 kHz
Warm up time to full accuracy	The shorter of 1 hour or twice the time since last warmed up
Settling time following change to the output	3 seconds maximum
Nominal angle between voltage phases	120 °
Nominal angle between voltage and current of a phase	0 °
Phase angle setting	0 ° to 359.99 °
Phase angle setting resolution	0.01 °

## Electrical Specifications

The product specifications describe the Absolute Instrumental Uncertainty of the Product. The product specifications include stability, temperature, and humidity; within specified limits, linearity, line and load regulation, and the reference standard measurement uncertainty. The product specifications are stated at a confidence limit of 99 %, k=2.58, normally distributed.

### Temperature Coefficient

Add 0.1x spec /°C for temperature ranges outside of Tcal  $\pm 2$  °C. For example, for Tcal = 23 °C, the specification at 11 °C and 35 °C is 2 times the nominal specification.

### Voltage

#### Voltage Channel Maximum Capacitive Loading for Output Stability

The voltage output remains stable up to a 100 nF load but may not be able to drive that capacitance at all voltage/frequency/harmonic combinations due to burden current limitations.

#### Voltage Range Limits and Burden

Range	1.0000 V to 10 V	10.0001 V to 30 V	30.001 V to 70 V	70.001 V to 140 V	140.001 V to 280 V <sup>[5]</sup>	280.001 V to 600 V <sup>[1]</sup>
Maximum Burden Current (peak) 40 Hz - 70 Hz <sup>[2][4]</sup>	141 mA	283 mA	424 mA	424 mA	283 mA	85 mA
Maximum Burden Current (RMS) 40 Hz - 70 Hz <sup>[2][4]</sup>	100 mA	200 mA	300 mA	300 mA	200 mA	60 mA
Maximum Burden Current (RMS) dc, 15 Hz to 40 Hz, 70 Hz to 1000 Hz <sup>[2][4]</sup>	100 mA	200 mA	200 mA	200 mA	150 mA	50 mA <sup>[3][4]</sup>
<p>[1] 600 V range is ac only, and limited to the fundamental frequency, for example. no additional harmonics can be generated.</p> <p>[2] Sum of all currents from three phases is limited to 400 mA RMS.</p> <p>[3] 600 V range cannot output dc.</p> <p>[4] Maximum burden current is reduced in Power Harmonic, Power Interharmonics, and Dip/Swell modes by a factor of 0.707 times the values shown. For example, the maximum burden current for a 10 V, 50 Hz harmonic output is 70.7 mA.</p> <p>[5] The 280 V range can be range-locked to output 71 V to 280 V using the Setup menu. When range-locked, limits are as shown for this range.</p>						

**Voltage Sine Amplitude**

Ranges	Frequency	1-Year Specification, Tcal $\pm 2$ °C $\pm$ (% of output + V)	
1.0000 V to 10.0000 V	15 Hz to 40 Hz	0.016	1 mV
	40 Hz to 70 Hz	0.012	1 mV
	70 Hz to 1 kHz	0.016	1 mV
10.0001 V to 30.000 V	15 Hz to 40 Hz	0.016	3 mV
	40 Hz to 70 Hz	0.012	3 mV
	70 Hz to 1 kHz	0.016	3 mV
30.001 V to 70.000 V	15 Hz to 40 Hz	0.016	7 mV
	40 Hz to 70 Hz	0.012	7 mV
	70 Hz to 1 kHz	0.016	7 mV
70.001 to 140.000 V	15 Hz to 40 Hz	0.016	14 mV
	40 Hz to 70 Hz	0.012	14 mV
	70 Hz to 1 kHz	0.016	14 mV
140.001 V to 280.000 V <sup>[1]</sup>	15 Hz to 40 Hz	0.016	28 mV
	40 Hz to 70 Hz	0.012	28 mV
	70 Hz to 1 kHz	0.016	28 mV
280.001 V to 600.000 V	20 Hz to 40 Hz	0.024	60 mV
	40 Hz to 70 Hz	0.016	60 mV
	70 Hz to 1 kHz	0.024	60 mV

[1] The 280 V range can be range-locked to output 71 V to 280 V with the specifications as stated for this range.

**Voltage DC**

Range	1-Year Specification, Tcal $\pm 2$ °C $\pm$ (% of output + V)	
1.0000 V to 10.0000 V	0.015	1 mV
10.0001 V to 30.0000 V	0.015	3 mV
30.001 V to 70.0000 V	0.015	7 mV
70.001 V to 140.000 V	0.015	14 mV
140.001 V to 280.000 V	0.015	28 mV

**Voltage Distortion**

<0.05 % 15 Hz to 200 kHz bandwidth

## Current

### Current Range Limits and Compliance

Range	5.000 mA to 300.000 mA	0.30001 A to 1.00000 A	1.00001 A to 2.00000 A	2.00001 A to 5.00000 A	5.0001 A to 10.0000 A	10.0001 A to 30.0000 A	90 mA to 90.0000 A <sup>[1]</sup>
Maximum Compliance Voltage (dc/peak) <sup>[3]</sup>	8	8	8	5	5	5	5
Maximum Compliance Voltage (RMS) 15 Hz to 400 Hz <sup>[3]</sup>	5.5	5.5	5.5	3.5	3.5	3.5	3.5
Maximum Compliance Voltage (RMS) 400 Hz to 1 kHz <sup>[3]</sup>	3.5	3.5	3.5	3.5	3.5	3.5	3.5
Maximum Inductive Load <sup>[2]</sup>	1 mH	1 mH	1 mH	1 mH	1 mH	1 mH	1 mH
<p>[1] 90 A range is available in the Current High I mode</p> <p>[2] Voltage compliance developed across inductive loads may limit the maximum current output being achieved at higher frequencies. The maximum frequency (Fmax) for a given load inductance and current is given by <math>F_{max} = V_c / (2 * \pi * I * L)</math>, where Vc is the maximum RMS compliance voltage.</p> <p>[3] Maximum compliance voltage is reduced in Power Harmonic, Power Interharmonic, and Dip/Swell modes by 0.707 times the values shown above. For example, the maximum compliance voltage for a 1 A, 50 Hz harmonic output is 3.89 V.</p>							

### Current Duty Cycle

The table below gives the duty cycle for permitted ON/OFF times for current outputs >20 A.

ON/OFF Duty Cycle for Current outputs > 20 A		
Ambient Temperature	ON Period (minutes)	OFF Period <sup>[1]</sup> (minutes)
5 to 15 °C	No limit	-
15 to 20 °C	15	8
20 to 25 °C	10	7
25 to 30 °C	6	6
30 to 35 °C	4	4
35 to 40 °C	3	3
[1] OFF Period defined as Standby or a non-current output.		

**Current Sine Amplitude**

Range (Amps)	Frequency	1-Year Specification, Tcal $\pm 2$ °C $\pm$ (% of output + A)	
5.000 mA to 300.000 mA	15 Hz to 40 Hz	0.021	60 $\mu$ A
	40 Hz to 70 Hz	0.0175	30 $\mu$ A
	70 Hz to 1 kHz	0.021	60 $\mu$ A
0.30001 A to 1.00000 A	15 Hz to 40 Hz	0.021	200 $\mu$ A
	40 Hz to 70 Hz	0.0175	100 $\mu$ A
	70 Hz to 1 kHz	0.021	200 $\mu$ A
1.00001 A to 2.00000 A	15 Hz to 40 Hz	0.021	400 $\mu$ A
	40 Hz to 70 Hz	0.0175	200 $\mu$ A
	70 Hz to 1 kHz	0.021	400 $\mu$ A
2.00001 A to 5.00000 A	15 Hz to 40 Hz	0.021	1 mA
	40 Hz to 70 Hz	0.0175	500 $\mu$ A
	70 Hz to 1 kHz	0.021	1 mA
5.0001 A to 10.0000 A	15 Hz to 40 Hz	0.028	2 mA
	40 Hz to 70 Hz	0.021	1.5 mA
	70 Hz to 1 kHz	0.04	2 mA
10.0001 A to 30.0000 A	15 Hz to 40 Hz	0.035	6 mA
	40 Hz to 70 Hz	0.0245	4.5 mA
	70 Hz to 1 kHz	0.05	6 mA
90 mA to 90.0000 A <sup>[1]</sup>	15 Hz to 40 Hz	0.035	18 mA
	40 Hz to 70 Hz	0.0245	13.5 mA
	70 Hz to 1 kHz	0.05	18 mA

[1] 90 A range is available in the Current High I mode

**Current DC**

Range	1-Year Specification, Tcal $\pm 2$ °C $\pm$ (% of output + A)	
5.000 mA to 300.000 mA	0.0175	30 $\mu$ A
0.30001 A to 1.00000 A	0.0175	100 $\mu$ A
1.00001 A to 2.00000 A	0.0175	200 $\mu$ A
2.00001 A to 5.00000 A	0.0175	500 $\mu$ A
5.0001 A to 10.0000 A	0.021	1.5 mA
10.0001 A to 30.0000 A	0.0245	4.5 mA
90 mA to 90.0000 A <sup>[1]</sup>	0.0245	13.5 mA

[1] 90 A range is available in the Current High I mode

**Current Distortion**

<0.1 %, 15 Hz to 200 kHz bandwidth

**Current Output Isolation (high or low terminal)**

450 V peak maximum above earth ground. The current output terminals must only be energized by the Product voltage output terminals.

## Voltage from the Current Terminals (DC and Sine Wave Only)

### Range Limits and Impedances

Range	1.000 mV to 20.000 mV	20.001 mV to 330.000 mV	0.33001 V to 5.00000 V
Source Impedance	1 $\Omega$	1 $\Omega$	18 $\Omega$
Minimum load impedance to maintain specification	25 k $\Omega$	25 k $\Omega$	450 k $\Omega$

### Voltage from Current Terminals

Range	Frequency	1-Year Specification, Tcal 2°C $\pm$ (% of output + V)	
1.000 mV to 20.000 mV	dc	0.05	20 $\mu$ V
	15 Hz to 400 Hz	0.05	20 $\mu$ V
20.001 mV to 330.000 mV	dc	0.05	200 $\mu$ V
	15 Hz to 400 Hz	0.05	200 $\mu$ V
0.33001 V to 5.00000 V	dc	0.05	1 mV
	15 Hz to 400 Hz	0.05	1 mV

Note: Specifications apply when measured with devices that have  $\leq$  100 kHz bandwidth.

### Voltage from Current Terminals, Distortion

<0.1 % + 100  $\mu$ V, 15 Hz to 200 kHz bandwidth

### Phase and Power Factor (Sine Wave Outputs)

Phase range	0.0 $^\circ$ to 359.99 $^\circ$
Frequency range	15 Hz to 1 kHz <sup>[1]</sup>
Phase resolution	0.01 $^\circ$
Power factor range	-1 to +1 (Lead, Lag)
Power factor resolution	0.001
Power factor accuracy	(1 - cos ( $\varphi$ +d $\varphi$ )/cos $\varphi$ ) where $\varphi$ is the phase in degrees and d $\varphi$ is the phase specification in degrees.
[1] Settling time for phase is typically <3 seconds, except for 15 Hz to 40 Hz which can be up to 30 seconds.	

### Current to Voltage Phase

For All Voltage Outputs (3 V to 600 V) <sup>[1]</sup>		
Current Output	Frequency	1-Year Specification, Tcal $\pm$ 2 $^\circ$ C
0.005 A to 0.099999 A	15 Hz to 70 Hz	0.05 $^\circ$ <sup>[2]</sup>
	70 Hz to 400 Hz	0.1 $^\circ$
	400 Hz to 1 kHz	0.4 $^\circ$
0.1 A to 10 A	15 Hz to 40 Hz	0.03
	40 Hz to 70 Hz	0.01 $^\circ$
	70 Hz to 400 Hz	0.1 $^\circ$
	400 Hz to 1 kHz	0.4 $^\circ$
10.0001 A to 30 A	15 Hz to 70 Hz	0.05 $^\circ$
	70 Hz to 400 Hz	0.1 $^\circ$
	400 Hz to 1 kHz	0.4 $^\circ$

[1] For < 3 V outputs from the Voltage channel, specification is the larger of 0.05  $^\circ$  or the value shown.

[2] For currents between 8 mA and 30 mA, the specification is 0.1  $^\circ$  for 15 Hz to 70 Hz. For currents < 8 mA, the specification is 0.4  $^\circ$  for 15 Hz to 400 Hz, and 1.0  $^\circ$  for 400 Hz to 1 kHz.

## Voltage from Current Terminals, Phase

For All Voltage Outputs (3 V to 600 V) <sup>[1]</sup>		
Ranges	20 mV, 330 mV, 5 V	
Voltage Output	Frequency	1-Year Specification, Tcal +/-2 ° C
<12 % of Range	15 Hz to 70 Hz	0.1 °
	70 Hz to 400 Hz	0.1 °
	400 Hz to 1 kHz	0.4 °
12 to 40 % of Range	15 Hz to 70 Hz	0.05 °
	70 Hz to 400 Hz	0.1 °
	400 Hz to 1 kHz	0.4 °
>40 % of Range	15 Hz to 40 Hz	0.03 °
	40 Hz to 70 Hz	0.01 °
	70 Hz to 400 Hz	0.1 °
	400 Hz to 1 kHz	0.4 °

[1] For < 3 V output from the Voltage channel, the specification is the larger of 0.05 ° or the value shown.

## Voltage to Voltage Phase

For All Voltage Ranges (3 V to 600 V) <sup>[1]</sup>	
Frequency	1-Year Specification, Tcal ±2 ° C
15 Hz to 40 Hz	0.03 °
40 Hz to 70 Hz	0.01 °
70.001 Hz to 400 Hz	0.1 °
400.001 Hz to 1 kHz	0.4 °

[1] For < 3 V outputs, specification is the larger of 0.05 ° or the value shown.

## Power

The power specifications below are valid for sinusoidal outputs for voltage, current, and frequencies shown. They are not valid when any harmonics, modulation (flicker), interharmonics, or dips/swells are applied.

To calculate the power specification for any specific voltage, current, and power factor outputs, use this formula:

$$dP = \sqrt{(dV^2 + dI^2 + dPF^2 + 0.01^2)} \text{ (\%)}$$

where dV is the specification of the voltage, dI is the specification of the current, dPF is the specification of the power factor; all expressed as a %. The 0.01 term is due to the interaction of voltage and current during simultaneous outputs.

Example calculations for 40 Hz to 70 Hz outputs:

Output 230 V, 20 A, PF = 1. 230 V has a specification of (0.012 % of output + 28 mV) or 0.024 %. 20 A has a specification of (0.0245 % + 4.5 mA), or 0.047 %. The phase specification for this output is 0.05 °. At PF = 1 the power factor specification is 0.0000 %.

Applying the power specification formula, this gives

$$\sqrt{(0.024^2 + 0.047^2 + 0.00^2 + 0.01^2)} = 0.054 \%$$

### Note

*This example is for a single phase output. The output will be 4600 W ± 2.484 W. For a three phase output, the specification is also 0.054 %. The total output is 13800 W ± 7.452 W.*

Output 115 V, 3 A, PF = 0.8. 115 V has a specification of (0.012 % of output + 14 mV) or 0.024 %. 3 A has a specification of (0.0175 % + 500 μA), or 0.034 %. The phase specification for this output is 0.01 °. At PF = 0.8 the power factor specification is 0.0131 %.

Applying the power specification formula, this gives

$$\sqrt{(0.024^2 + 0.034^2 + 0.0131^2 + 0.01^2)} = 0.045 \%$$

Output 280 V, 5 A, PF = 0.5. 280 V has a specification of (0.012 % of output + 28 mV) or 0.022 %. 5 A has a specification of (0.0175 % + 500 μA), or 0.028 %. The phase specification for this output is 0.01 °. At PF = 0.5 the power factor specification is 0.0302 %.

Applying the power specification formula, this gives

$$\sqrt{(0.022^2 + 0.028^2 + 0.0302^2 + 0.01^2)} = 0.047 \%$$



**Sinusoidal Power Specification at 40 Hz to 70 Hz, Power Factor 1.0 (%)**

Current Output	Voltage Output					
	10 V	30 V	70 V	140 V	280 V	600 V
1.00000 A	0.037	0.037	0.037	0.037	0.037	0.039
5.00000 A	0.037	0.037	0.037	0.037	0.037	0.039
10.0000 A	0.043	0.043	0.043	0.043	0.043	0.046
30.0000 A	0.046	0.046	0.046	0.046	0.046	0.048

**Sinusoidal Power Specification at 40 Hz to 70 Hz, Power Factor 0.8 (%)**

Current Output	Voltage Output					
	10 V	30 V	70 V	140 V	280 V	600 V
1.00000 A	0.039	0.039	0.039	0.039	0.039	0.041
5.00000 A	0.039	0.039	0.039	0.039	0.039	0.041
10.0000 A	0.045	0.045	0.045	0.045	0.045	0.047
30.0000 A	0.080	0.080	0.080	0.080	0.080	0.081

**Sinusoidal Power Specification at 40 Hz to 70 Hz, Power Factor 0.5 (%)**

Current Output	Voltage Output					
	10 V	30 V	70 V	140 V	280 V	600 V
1.00000 A	0.047	0.047	0.047	0.047	0.047	0.049
5.00000 A	0.047	0.047	0.047	0.047	0.047	0.049
10.0000 A	0.053	0.053	0.053	0.053	0.053	0.055
30.0000 A	0.158	0.158	0.158	0.158	0.158	0.158

**DC Power Specification (%)**

DC power is calculated as  $dP = \sqrt{(dV^2 + dI^2 + 0.01^2)} (\%)$

Current Output	Voltage Output				
	10 V	30 V	70 V	140 V	280 V
5.00000 A	0.038	0.038	0.038	0.038	0.038
10.0000 A	0.045	0.045	0.045	0.045	0.045
30.0000 A	0.048	0.048	0.048	0.048	0.048

**Multimeter**

Function	Measuring Range	1-year Specification, Tcal $\pm 2^\circ\text{C}$ (% of reading + floor)	Resolution
DC Voltage	0 V to $\pm 12$ V	0.01 % + 1.2 mV	100 $\mu\text{V}$
DC Current	0 mA to $\pm 25$ mA	0.01 % + 2.5 $\mu\text{A}$	100 nA
Frequency	1 Hz to 15 kHz	0.005 %	10 $\mu\text{Hz}$ to 0.1 Hz

Note: The settling time to full accuracy is up to 4 seconds.

**IN2 Input**

Input IN2 (trigger, synchronization)	
Max frequency	10 kHz
Input low level max	0.8 V
Input high level min	3.5 V

**Energy (6003A/E Energy Option)****Pulse Inputs (IN1)**

Max frequency	1 MHz (400 Hz with Input Filter On)
Min pulse width	500 ns
Max counts	5 000 000 000
Voltage high and low limits	low level max 0.8 V, high-level min. 3.2 V

**Energy Pulse Output**

Drive	Open collector
Frequency range	0.02 Hz to 1 MHz
Frequency specification	50 ppm of output
External pull-up	150 $\Omega$ , selectable on/off
Sink current	100 mA

**Energy**

Time range	1 to 1 0000 0000 seconds
Time resolution	0.1 seconds
Time interval specification	0.01 % of time interval + 0.1 seconds

**Test Duration**

Maximum test duration	1000 hours
-----------------------	------------

**Power Quality (6003A/PQ Power Quality Option)****Voltage and Current Sinusoidal and Rectangular Modulation Flicker Specification**

Modulation depth	0 to 30 %
Modulation depth specification	0.2 % of modulation depth
Modulation depth setting resolution	0.001 %
Shape of modulation envelope	Rectangular or Sinusoidal
Duty cycle (shape = rectangular)	1 % to 99 %
Modulating frequency specification	50 ppm of output
Modulation frequency range	0.001 Hz to 50 Hz
RMS amplitude specification	0.2 % of range
Fundamental frequency range	15 Hz to 1 kHz
Harmonic (2 to 63) frequency range	30 Hz to 5 kHz
Note:	For a given modulation %, the output signal swings between (output setting + modulation %) and (output setting - modulation %). The Fluke 6100 Series Electrical Power Standard defines modulation as $\Delta V/V\%$ , where its output signal swings between (output setting + $\frac{1}{2} \Delta V/V\%$ ) and (output setting - $\frac{1}{2} \Delta V/V\%$ ). To get the same modulation as the 6100 series, set the 6003A modulation to $\frac{1}{2}$ the $\Delta V/V\%$ setting of the 6100.

### Harmonics and Interharmonic

Interharmonics are available on voltage and current outputs.

Fundamental harmonic frequency range	15 Hz to 1 kHz
Fundamental harmonic amplitude specification	±0.2 % of range
Harmonics (2 to 63) frequency range	30 Hz to 5 kHz
Interharmonic frequency range	15 Hz to 1 kHz
Maximum harmonic number	63
Number of interharmonic products	1
Frequency specification	±0.005 % of output
Fundamental harmonic phase specification <sup>[2]</sup>	15 Hz to 70 Hz: 0.2 °
	70 Hz to 400 Hz: 0.5 °
	400 Hz to 1 kHz: 1 °
Harmonics (2 to 63) phase specification	5 μs <sup>[1]</sup>
Voltage harmonic and interharmonic amplitude specification ( 1 V to 280 V)	30 Hz to 3 kHz: 0.1 % of range
	3 kHz to 5 kHz: 0.2 % of range
Current harmonic and interharmonic amplitude specification (5 mA to 2 A)	30 Hz to 3 kHz: 0.1 % of range
	3 kHz to 5 kHz: 0.2 % of range
Current harmonic and interharmonic amplitude specification (2 A to 10 A)	30 Hz to 3 kHz: 0.2 % of range
	3 kHz to 5 kHz: 0.4 % of range
Current harmonic and interharmonic amplitude specification (10 A to 30 A)	30 Hz to 3 kHz: 0.2 % of range
	3 kHz to 5 kHz: 0.8 % of range
Maximum amplitude of harmonic products	30 % of RMS output value
Harmonic resolution of harmonic products	0.001 %
Noise and Distortion	-60 dB
<p>[1] Into resistive loads. For current outputs, harmonics &gt;3 kHz and/or &gt;1.5 V rms compliance on the composite waveform, the specification is 10 μs. The phase accuracy of a given harmonic is given by <math>P = 5 \mu s / (1/f) \times 360</math> where P = phase accuracy in degrees, f = harmonic frequency</p> <p>[2] Fundamental Interharmonic phase specifications are the same except 15 Hz to 70 Hz is 0.4 degrees.</p>	

### Dip/Swell

Although Dips and Swells are primarily voltage phenomena, the Product provides the same facility on its current output.

AC voltage range	0.1 V to 280 V
AC current range	1 mA to 30 A
Amplitude accuracy	0.2 % of range <sup>[1]</sup>
Frequency range	15 Hz to 1 kHz
Timing <sup>[2]</sup>	
T1 range	0 s to 60 s
T2 range	0.1 ms to 60 s
T3 range	2 ms to 60 s
T4 range	0.1 ms to 60 s
T5 range	0 s to 60 s
<p>[1] Range is determined by the highest value of the output signal</p> <p>[2] T1 + T5 &gt; 2 ms</p>	

#### Note

*Maximum voltage burden and current compliance is reduced in Power Quality functions. See Voltage Range Limits and Burden and Current Range Limits and Compliance above.*

## Change #2, 390

On page 1-13, in the *Harmonics and Interharmonic* table, replace the first column of the 11th row with:

Current harmonic and interharmonic amplitude specification (5 mA to 2 A)

On page 3-13, under *Connection/Disconnection of Output Terminals*, replace the 5<sup>th</sup> bullet with:

- Output voltage exceeds 30 V. This occurs if the output value is changed from <30 V to a new value >30 V.

On page 3-14, replace *Control Sequence when the Output Voltage is >100 V is Selected* with:

### *Control Sequence when the Output Voltage is >30 V is Selected*

If the output terminals are currently connected and the output is < 30 V, they will be disconnected when output voltage > 30 V is selected. Push **OPER** to reconnect the output signal to the output terminals. After **OPER** is pushed, the Operate LED is illuminated. Once the output voltage is at 30 V or greater, subsequent changes to the output voltage will not disconnect the output terminals. Voltages < 30 V and any frequency can be set without the outputs being disconnected. Independent of this connect/disconnect sequence is the appearance of the symbol that informs that a life-threatening voltage is present or will be present at the output terminals. This symbol appears in the information section of the display whenever a voltage 50 V or greater is selected.

On page 4-6, following step number 4, add new steps 5 and 6 and renumber the previous 5 and 6 to 7 and 8.

5. Phase rotation sets the Product to either a positive or negative sequence for the phases.
6. 280 V range lock sets all output voltages from 71 V to 280 V to come from only the 280 V range. This is a useful when powering up units-under-test (UUTs) with the Product and the Product range change causes the UUT to momentarily power off.

On page 4-10, under *Activate the Output Terminals*, replace the 4<sup>th</sup> bullet with:

- If the output voltage exceeds 30 V. See below - *Control Sequence when Output Voltage over 30 V is Selected*.

On page 4-11, replace the ***Control Sequence when Output Voltage >100 V*** section with:

### ***Control Sequence when Output Voltage >30 V***

If the output terminals are currently connected and the output is < 30 V, they will be disconnected when output voltage > 30 V is selected. Push **OPER** to reconnect the output signal to the output terminals. After **OPER** is pushed, the Operate LED is illuminated. Once the output voltage is at 30 V or greater, subsequent changes to the output voltage will not disconnect the output terminals. Voltages < 30 V and any frequency can be set without the outputs being disconnected. Independent of this connect/disconnect sequence is the appearance of the symbol that informs that a life-threatening voltage is present or will be present at the output terminals. This symbol appears in the information section of the display whenever a voltage 50 V or greater is selected.

On page 4-13, under **Generating Electric Power**, replace the Current Setting range with:

Current setting range: 5 mA to 30 A (each channel) or 90 mA to 90 A  
(High I mode, one channel)

On page 4-28, under **Generate Electric Energy (Available with 6003A/E Energy Option installed)** replace with:

Current setting range: 5 mA to 30 A (each channel), 90 mA to 90 A (High I mode)

On page 4-35, under **Generate Current**, replace the Current Setting range with:

Current setting range: 5 mA to 30 A

On page 4-41, under **Use the Product to Power Energy Meters**, replace the last sentence in the paragraph with the following:

When the Product voltage outputs are used to power any Unit Under Test (UUTs), make sure to not exceed the rated burden current limits for the voltage range(s) used. Note that many UUTs have high-peak current demands upon their power-up, which may cause the Product to trip into Standby.

On page 5-36, following **Using Replaceable Parts** add:

To update the firmware (FW) on the 6003A:

1. Download and install the 6003A firmware update tool. This can be downloaded from [www.flukecal.com](http://www.flukecal.com) in the Software downloads section. To install, open the "setup.exe" file. The installation will take a few minutes to complete.
2. Once installed, open the firmware update tool named "uploader.exe".
3. Set the 6003A baudrate to 9600 in the setup menu.
4. Select the comm port.
5. Use the file explorer to select the firmware source file.

**⚠ Caution**

**Do not interrupt the firmware update during this time. When complete, a dialog box is shown.**

6. Power cycle the 6003A.
7. Once powered on, check the FW version in the Setup menu.

The FW update is complete.