

Manual Supplement


Manual Title:	RUSKA 7615 Users	Supplement Issue:	3
Part Number:	3952199	Issue Date:	6/17
Print Date:	November 2010	Page Count:	2
Revision/Date:			

This supplement contains information necessary to ensure the accuracy of the above manual.



Change #1, 455, 459

On page 1-3, add the following to the **Symbols** table:

Symbol	Description
	Conforms to relevant South Korean EMC Standards.

On page A-3, under **Specifications**, replace EMC with:

Electromagnetic Compatibility (EMC)

International IEC 61326-1 Basic Electromagnetic Environment

CISPR 11: Group 1, Class A

Group 1: Equipment has intentionally generated and/or uses conductively-coupled radio frequency energy that is necessary for the internal function of the equipment itself.

Class A: Equipment is suitable for use in all establishments other than domestic and those directly connected to a low-voltage power supply network that supplies buildings used for domestic purposes. There may be potential difficulties in ensuring electromagnetic compatibility in other environments due to conducted and radiated disturbances.

Emissions that exceed the levels required by CISPR 11 can occur when the equipment is connected to a test object.

Korea (KCC)..... Class A Equipment (Industrial Broadcasting & Communication Equipment)

Class A: Equipment meets requirements for industrial electromagnetic wave equipment and the seller or user should take notice of it. This equipment is intended for use in business environments and not to be used in homes.

USA (FCC)..... 47 CFR 15 subpart B. This product is considered an exempt device per clause 15.103.

Note

The Product can show some control sensitivity to moderate or severe electromagnetic fields of certain frequencies. In the presence of radiated EM disturbances, with frequencies of 400 MHz to 850 MHz and with amplitude >550 mV/m to a maximum of 1 V/m, add 0.02 % FS to the accuracy and stability specification.

Change #2, 502

On page A-3, under **Specifications**, replace Electrical Power, Ingress Protection and Electrical Safety and add:

Ingress Protection IEC 60529: IP20

Operating EnvironmentIndoor use


Altitude<2000 m

Safety

MainsIEC 61010-1: Overvoltage Category II, Pollution Degree 2

AC Mains Supply.....115/230 VAC, 50/60 HZ, single phase.

On page 1-3, in the **Symbols** table add:

	Consult user documentation.
---	-----------------------------

On page 1-2, add the following **Warnings**:

⚠⚠ Warning

To prevent possible electrical shock, fire, or personal injury:

- **Read all safety information before you use the Product.**
- **Do not alter the Product and use only as specified, or the protection supplied by the Product can be compromised.**
- **Do not use the Product if it operates incorrectly.**
- **Use this Product indoors only.**
- **Use only the mains power cord and connector approved for the voltage and plug configuration in your country and rated for the Product.**

On page 4-1, add the following **Warnings**:

⚠⚠ Warning

To prevent possible electrical shock, fire, or personal injury:

- **Connect an approved three-conductor mains power cord to a grounded power outlet.**
- **Do not put the Product where access to the mains power cord is blocked.**
- **Do not touch exposed metal on banana plugs, they can have voltages that could cause death.**
- **Make sure that the Product is grounded before use.**

On page 6-1, add the following **Warning**:

⚠⚠ Warning

To prevent possible electrical shock, fire, or personal injury:

- **Disconnect the mains power cord before you remove the Product covers.**